



**NAME:** LED Retrofit Kit

**P/N:** SNC-CLH-95W1A1Y

Note : The Letter Y in P/N stands for Lamp base type, "-E" for E39 lamp base, "-EX" for EX39 lamp base.

### Advantage

- UL、CUL、DLC certificate
- PHILIPS LUMILEDS chip, high CRI.
- 90\*150 degree, TYPE III.
- Internal driver, input voltage AC100-277V.
- E39、EX39 lamp base. Single SUNON fan.
- Lamp Base: 270 degree rotated.
- Automatically Power-Reducing Function: Power reduces gradually when driver's temperature reaches 50°C. When the heat sink of led reaches 90°C, there will no power reduction any more. And power will reduce to 78% of the origin.
- New style and high efficient wide-range input.
- Long lifespan and good heat dissipation.
- Direct replacement for Metal Halide, easy Installation.
- Fits many different fixtures to replace traditional lamps.



### Application

LED Retrofit Kit make it simple to replace: parking lot lighting, shoebox lighting, street lighting, flood lighting, wall pack lighting, and canopy lighting etc.

Specifications Subject To Change Without Notice